



DOCTOR CHARGE 130 230V 12V/24V



Overview

DOCTOR CHARGE 130 230V 12V/24V

cod. 807599

Electronic BATTERY MANAGER for total maintenance of WET, GEL, AGM, MF, PbCa, EFB and Li batteries at 12/24V and for support activities when intervening on vehicles in workshops, repair shops and car dealer premises.

The innovative Power Stream technology guarantees better performance, up to 50% more than traditional battery chargers.

The Pulse Tronic technology guarantees optimal battery charging over 8 phases.

Doctor Charge 130 carries out 5 functions:

1. automatic charge and maintenance of batteries with PULSE TRONIC technology, even in difficult environmental conditions (low temperatures);
2. battery tests such as voltage at terminals, starting capacity (CCA) and operational check of the vehicle alternator;
3. recovery of sulphated or very discharged batteries, and recovery of optimal operation with periodic regeneration;
4. stable power supply source for battery changes (to protect the on-board electronics), for diagnostic activities (operation checks carried out on the vehicles), for keeping the batteries of display vehicles in showrooms operational;
5. vehicles start.

Based on the SMPS (Switch Mode Power Supply) Technology. In case of black-outs or repetitive uses Doctor Charge 130 can set itself at the last settings carried out. Many protections available.

Fit with PFC device.

Technical data

| | | | | | |
|------------------------|----------------------------------|-------------------------|--|------------------|----------------------------|
| CODE | CODE 807599 | A_{EFF} | EFFECTIVE CHARGING CURRENT 140 / 70 A | W x H x L | DIMENSIONS 20 - 26 - 34 cm |
| V_{1PH} | SINGLE PHASE MAINS VOLTAGE 230 V | A_{IN} | RATED CHARGE CURR. EN60335-2-29 120 / 60 A | kg | WEIGHT 6 kg |
| F | MAINS FREQUENCY 50 / 60 Hz | A_{IVIC} | START CURRENT 1V/C EN60335-2-29 180 A | BAR CODE | EAN CODE 800489706429 1 |